

# Aluwave (PIR-sensor)

## Presence detection

### Description:

- Motion detector for luminaire installation.
- For automatic on/off switching of luminaires with electronic ballasts and LED drivers.
- Delay time for the on/off function can be set via switch.
- L-out for powering on/off luminaires. Max 3pcs drivers.
- L-out for powering corridor function(P1,P2) luminaires. No restrictions.

### Detection area:

- At a mounting height of 2m above the floor, the detection area will be 5m in diameter at floor level.

### Technical data:

- Power (output on): 0,5W
- Power (output off): 0,25W

### Settings (sensor)

#### Delay time:

- Switch location I 5 minutes
- Switch location II 15 minutes (default)

